


# DESCRIPTION


The ICE-420-EM-A from IOTA Engineering is a UL Listed fluorescent emergency ballast for use in cold-weather applications that allows the same fixture to be used for both normal and emergency operation. In the event of a power failure, the ICE-420-EM-A switches to the emergency mode and operates one or two of the existing lamps for 90 minutes. The ICE-420-EM-A can be used with 10W to 70W 4-pin compact fluorescent lamps, providing an initial output of up to 1300 lumens for one or two lamps, and features lamp selector leads for optimizing the light output for designated lamp types. The unit contains a battery, charger, and inverter circuit in a single can, in addition to temperature control circuitry protect the battery pack from freezing during normal AC operation and allows the battery pack to reach acceptable operating temperatures before reactivating the charging circuit. The ICE-420-EM-A provides 1/2" flex for wiring to the fixture or ballast compartment and test accessories. The test switch and charge indicator are provided for installation in a standard switch box for mounting adjacent to the fixture.

### SPECIFICATIONS

Input Voltage	(Dual) 120/277V, 60Hz
Input Wattage	
Wattage Draw (when heating element is on)	
Lamps Operated	
Emergency Operation (1)	10W-70W or (2) 10W-32W 90 minutes
Initial Illumination	
Operating Temp	-18° to 50° C
Battery	
Weight	
Approval	UL and CUL Listed

### DIMENSIONS





# ICE-420-EM-A

MODEL NO:

TYPE: \_

PROJECT:

COMMENTS:

INITIAL LUMEN OUTPUT

1300 Lumens

#### LAMPS OPERATED\*

П



(1) 10W-70W 4-PIN Compact (2) 10W-32W 4-PIN Compact \*Refer to Lumen Reference Chart for list of compatible lamps

#### **PRODUCT ADVANTAGES**

- Designed for outdoor paths of egress and freezing environments
- Internal Heating and Temperature Control protects the battery from freezing conditions
- Damp Location Rated
- Time Delay feature for compatibility with End-of-Lamp-Life circuitry
- Open Circuit Isolation protects unit when load is absent

#### **FEATURES**

- Will cold start and operate all specified lamps
- Long life high temperature recyclable Ni-Cad battery
- Galvanized steel case
- Includes test switch and charge indicator accessories
- For use with switched or unswitched fixtures
- 5-Year Warranty. See Warranty Page for details.
- Lamp selector leads optimize light output for desired lamp type
- Rated for use in damp locations, plenum, and recessed Type IC fixtures
- Meets or exceeds all NEC, IBC, and Life Safety Code Emergency Lighting Requirements
- RoHS Compliant
- International Voltage models available



IOTA REV 080315

# ICE-420-EM-A COLD WEATHER FLUORESCENT EMERGENCY BALLAST

### OPTIONS

# **TEST KIT CONFIGURATION**

O TBTS

O TWO-PIECE TEST SWITCH AND CHARGE INDICATOR

# **VOLTAGE RATINGS**

- 120/277V 60HZ (STANDARD)
- O 220V 50HZ
- 240V 60HZ
- O 120V 50HZ

### **INITIAL LUMEN RATINGS\***


LAMP	1 I AMP	2 LAMPS
		2 LAIVIE 3
13W PL CF 4-PIN	600	675
18W PL CF QUAD 4-PIN	600	950
26W PL CF QUAD 4-PIN	725	1200
32W PL CF QUAD 4-PIN	1050	1250
42W PL CF QUAD 4-PIN	1300	
57W PL CF QUAD 4 PIN	1160	
70W PL CF QUAD 4-PIN	1200	
F282 D/42 4-PIN	800	850
F382 D/42 4-PIN	850	1125


\*Rated lumens measured @ 25° C.

### **ICE-420-EM-A SAMPLE SPECIFICATION**

Emergency lighting shall be provided by using a fluorescent fixture and lamp(s) rated for exterior installation conditions equipped with an IOTA ICE-420-EM-A fluorescent emergency battery pack. The ICE-420-EM-A shall consist of a high temperature, maintenance-free nickel cadmium battery, charger board and an electronic circuit enclosed in a 13.3" x 2.4" x 1.5" vandal-resistant galvanized steel case. The unit is designed for installation on top of the fixture and is equipped with 1/2" flex for wiring to the fixture or ballast compartment. A long-life LED charge indicator light and test switch shall be included. The fluorescent EM pack shall operate one 10w-42w, 57w, or 70w or two 10w-32w twin, triple, quad tube, 2D or straight 4-pin fluorescent lamps. The ICE-420-EM-A shall provide reduced illumination for a minimum of 90 minutes in the emergency mode with a total initial output of 1300 lumens, and will feature lamp selector leads for optimizing light output for the designated lamp type. The ICE-420-EM-A shall have 3.5 watts of input power with the heating element off, 100 watts (.83 amps) with the heating element on, and a battery capacity of 24 watt hours. The ICE-420-EM-A is UL Listed and meets or exceeds all NEC and Life Safety Code Emergency Lighting Requirements. The ICE-420-EM-A is warranted for a full five (5) years from the date of purchase.

## **TEMPERATURE CONTROLS**





#### REMOTE MOUNTING

When battery packs are remote mounted, consult Customer Service for the maximum allowable distance between the battery pack and lamp(s).

IOTA REV 080315